# POWER YOUR FUTURE

# Weichai Generator LG400WP

# WP13D490E310

Prime Power: 400KW/500KVA

Standby Power: 440KW/550KVA



## GENERATING POWER SOLUTIONS

#### Increased availability for new operations

Reliable, robust and versatile generator. Ready to deliver power for a next job.

#### **Increased uptime during operations**

Once installed on the end-user-site, the generator will be ready to run: "peace of mind" operation.

#### Reduced transport and installation costs

The compact and robust design with integrated transport features enables faster and safer transport and installation.

#### Reduced service & maintenance costs

Longer service intervals.

Quicker and more efficient service jobs.

#### **Premium resale value**

Designed and built to last.



- Operate safely in accordance with proper operation manual.
- To prevent trouble and accidents perform daily and preventive maintenance checks without fail.

WEICHAI Series 20KVA--600KVA



# FUAN LONGKAI POWER CO.,LTD.

#### **Headquarters:**

Add: Wei 5 Road, Tiehu Industrial Zone, Fuan, Fujian, China

Tel:+86-0593-6309773 Fax:+86-0593-6586988

E-mail: sales@longkaipower.com Web: www.longkaipower.com



# **Technical Data**

Model		LG400WP
Rated prime power	kva	500
Rated standard power	kva	550
Rated voltage line to line	V	400/230
Rated current	Α	722
Maximun sound level	dB(@7m)	≤100

Engine-Weichai		
Model	V	/P13D490E310
Aspiration	Turbocharged and aftercooled	
Fuel system	mechanical pump	
No. cylinders		6 in line
Displacement	Liquid	12.54
Bore*Stroke	mm	127*165
Compression ratio		15
Rated speed	r/min	1500
Rated net power(with fan)	Kw	450
Governor type	mechanical speed governors	
Start Motor	V	24

Exhause System		
Exhause gas flow	L/s	2428
Exhause gas temp	° F (° C)	580
Max back pressure	in Hg	12

Aspiration System		
Max inlet pressure	kPa	≤3.5
Combustion volume	L/s	/
Air flow	L/sec	2336

Fuel System		
100% load(Prime power)	L/h	97.7
75% load(Prime power)	L/h	/
50% load(Prime power)	L/h	1
Fuel tank capacity	L	780

<b>Lubrication System</b>		
Oil capacity	L	30
Oil consumption	g/kwh	0.2
Oil pressure	kPa	330-550
(continuous operation)		

Cooling System		
Coolant capacity	L	25
Thermostat operation range	$^{\circ}$ C	76-88
Max water temperature	$^{\circ}\!\mathbb{C}$	98

Alternator		
Model	LONGKAI	LK544D
	STAMFORD H	CI544D-S5L1D-C4/S5L1S-C4
Phase		3
Voltage	V	400/230
Wiring Type	3 Pha	se 4 wire, Y type
Bearing		1
Power factor		8.0
Frequency	Hz	50
Prime power	KW	440
Exciter Type	Brushles	s, self-excitation

## **Controller-DEEPSEA**

Model DSE6120MK3

%

m

Protective functions:

Low oil pressure

Altitude

Voltage regulation

**Protection Grade** 

Insulation grade

- High water temperature
- High/low voltage
- High Engine Temperature and Overspeed.
- Voltage regulator frequency regulator
- Emergency stop
- Start failure



#### **Control Module Options**





- ■Auto generator control module
- ■Control module with" Three Remote Control" functions
- ■ATS auto load transfer screen
- Synchronising control modules
- ■Power output cabinet

LG400WP

±0.5

IP 23

H/H


≤1000




#### Standard Features

otariaara i oataroo
Engine(WEICHAI GROUP)
Radiator 50°C max,fans are driven by bel
24V charge alternator
Alternator: single bearing alternator IP23,
insulation class H/H
Standard auto control system
One set of air filter, fuel filter, oil filter
Main line circuit breaker/MCCB
Base fuel tank
Two 24V batteries, rac and cable
Exhaust system(Ripple flex exhaust pipe,
exhaust siphon, flange, muffler
User manual •

# Unit Dimensions(Basic unit)





## Options

Options		
Battery charge		0
Engine heater		$\circ$
Alternator heater		$\circ$
PMG		$\bigcirc$
Water oil separator		$\circ$
Daily fuel tank		$\circ$
Remote control panel		$\bigcirc$
Automatic transfer switch/AT	S	$\circ$
Switch box		$\bigcirc$
Standard: ●	Options:o	

# Warranty\*

# Weichai Engine

12 months from date of purchase and 1000 hours.

#### Generator

12 months from date of purchase or 1000 hours (whichever occurs first).



More information, pls refer to our web-site: www.longkaipower.com

Manufacturer reserves the right to make changes in model, technical specification, color, equipment and accessories without notice.